

## Verasys® Application Controller (VAC) Catalog Page

### Description

The Verasys® Application Controllers are part of the SMART Equipment Controller family. The Verasys Application Controllers run pre-engineered applications and provide the inputs and outputs required to monitor and control a wide variety of HVAC equipment.

Verasys Application Controllers operate on an RS-485 BACnet® MS/TP Bus as BACnet Advanced Application Controllers (B-AACs). The controllers integrate into Johnson Controls® and third-party BACnet systems.

Verasys Application Controllers include an integral real-time clock that enables the controllers to monitor and control schedules, calendars, and trends. The controllers can operate for extended periods of time as stand-alone controllers when they are disconnected from the system network.

Refer to the *Verasys System Product Bulletin (LIT- 12012342)* and controller application guides for more information about controllers that have applications loaded in them.

### Verasys Application Controllers



### Repair Parts

If the Verasys Equipment Controller fails to operate within its specifications, replace the unit. For a replacement unit, contact the nearest Johnson Controls sales representative.

### Selection Chart

Code Number	Description
LC-VAC1000-0	18 point 24 VAC Application Controller with no application loaded
LC-VAC1001-0	18 point 24 VAC Application Controller with lighting controller application loaded
LC-VAC1002-0	18 point 24 VAC Application Controller with input and output controller application loaded
LC-VAC1100-0	18 point 240 VAC Application Controller with no application loaded
LC-VAC3000-0	32 point 24 VAC Application Controller with no application loaded
LC-VLP100-0	16in. x 20in. panel with LC-VAC1001-0 Controller, with 96 VA power supply
LC-VLP110-0	24in. x 24in. panel with LC-VAC1001-0 Controller, with pilot relays, without contactors
LC-VLP120-0	24in. x 36in. panel with LC-VAC1001-0 Controller, with pilot relays, with contactors
LC-IOP100-0	16in. x 20in. panel with LC-VAC1002-0, with 96 VA power supply

### Technical Specifications

#### LC-VAC100x-0 (Part 1 of 3)

<b>Product Code Numbers</b>	LC-VAC100x-0 Verasys 18 point 24 V Application Controller with display
<b>Supply Voltage</b>	24 VAC, 20 VAC minimum and 30 VAC maximum, 50/60 Hz, power supply Class 2 (North America), Safety Extra-Low Voltage (SELV) (Europe)
<b>Power Consumption</b>	20 VA maximum for LC-VAC100x-0 <b>Note:</b> VA rating does not include any power supplied to the peripheral devices connected to Binary Outputs (BOs) or Configurable Outputs (COs). This can consume up to 12 VA for each BO or CO; for a possible total consumption of an additional 60 VA maximum.
<b>Ambient Conditions</b>	<b>Operating:</b> -20°C to 70°C (-4°F to 158°F); 10 to 95% RH noncondensing; Pollution Degree 2 <b>Storage:</b> -40°C to 85°C (-40°F to 185°F); 5 to 95% RH noncondensing.
<b>Addressing</b>	<b>BACnet® MS/TP:</b> Valid field controller device addresses 4–127 Device addresses 0–3 and 128–255 are reserved and not valid field controller addresses. <b>N2:</b> Valid field controller device addresses 1 to 255


## Verasys® Application Controller (VAC) Catalog Page (Continued)

### LC-VAC100x-0 (Part 2 of 3)

<b>Communications Bus</b>	<b>BACnet® MS/TP, ModBus and N2 through RS-485:</b> <ul style="list-style-type: none"> <li>• 3-wire System Bus between the supervisory controller and field controller</li> <li>• 3-wire Sensor Bus between controller, network sensors and other sensor/actuator devices, includes a lead to source 15 VDC supply power from controller to bus devices</li> <li>• 3-wire one Modbus communication half-duplex (Master RTU port)</li> </ul>
<b>Processor</b>	RX631 Renesas® 32-bit microcontroller
<b>Memory</b>	16 MB flash memory and 8 MB RAM
<b>Input and Output Capabilities</b>	<p><b>Five universal inputs:</b> User-configurable, 3 available modes:</p> <ul style="list-style-type: none"> <li>• Voltage input: 0 to 10 VDC</li> <li>• Current sense input: 4 to 20 mA</li> <li>• Resistive inputs/dry contact inputs</li> </ul> <p><b>Four binary inputs:</b> Defined as Dry Contact maintained or Pulse Counter/Accumulator Mode</p> <p><b>Three configurable outputs:</b> User-configurable, 2 available modes:</p> <ul style="list-style-type: none"> <li>• Analog output: 0 to 10 VDC, 10 mA</li> <li>• Triac output: 24 VAC, 0.5 A (externally sourced powered)</li> </ul> <p><b>One utility output power port (24- OUT):</b> Ability to deliver 24 VAC</p> <p><b>Four binary outputs (relays):</b> Single-Pole, Single-Throw. Dry contacts rated 240 VAC.</p> <ul style="list-style-type: none"> <li>• UL: 240 VAC 5 A Resistive, 1.9 LA/11.1LRA, D300 Pilot Duty, 70°C/158°F (30,000 cycles)</li> <li>• IEC: 240 VAC 3 A Resistive, 3A Inductive, Cos=0.6, -20°C to 70°C (-4°F to 158°F) (100,000 cycles)</li> </ul> <p><b>Note:</b> Reference all relay commons to the same pole of the supply circuit.</p> <p><b>Two Binary Outputs (Triacs):</b> Output: 24 VAC or 240 VAC, 0.5 A (externally powered)</p> <p><b>Note:</b> Reference all triac commons to the same pole of the supply circuit.</p>
<b>Analog Input/Analog Output Resolution and Accuracy</b>	<p>Analog input: 12-bit resolution</p> <p>Analog output: 15-bit resolution; +/- 200 mV accuracy in 0 to 10 VDC applications</p>
<b>Terminations</b>	<p>Input/output: Fixed spade terminals</p> <p>Sensor/System/Modbus: 4-wire and 3-wire pluggable screw terminal blocks</p> <p>Sensor bus tool port: RJ-12 6-pin modular jack</p> <p><b>Field install option:</b></p> <p>Input/output: Fixed solder terminals</p> <p>Sensor/System/Modbus: 4-wire and 3-wire pluggable screw terminal blocks</p> <p>Sensor Bus tool port: RJ-12 6-pin modular jack</p>
<b>Mounting</b>	<p>Horizontal on single 35 mm DIN rail mount is preferred, or screw mount on flat surface with three integral mounting clips on controller</p> <p>Mount the controller on a wall or DIN rail inside an enclosure rated at least IP20.</p>
<b>Housing</b>	Enclosure material: Polycarbonate Lexan SABIC EXL9330
<b>Dimensions (H x W x D)</b>	164 mm x 125 mm x 53 mm (6.45 in. x 4.92 in. x 2.08 in.) excluding terminals and mounting clips
<b>Weight</b>	0.5 kg (1.1 lb)

## Verasys® Application Controller (VAC) Catalog Page (Continued)

### LC-VAC100x-0 (Part 3 of 3)

	<b>United States:</b> cULus Listed, File E107041, CCN PAZX, UL 916, Energy Management Equipment FCC Compliant to CRF47, Part 15, Subpart B, Class A
	<b>Canada:</b> cULus Listed, File E107041, CNN PAZX7 CAN/CSA C22.2 No.205, Signal Equipment Industry Canada Compliant, ICES-003
	<b>Europe:</b> Johnson Controls declares that this product is also in compliance with the essential requirements and other relevant provisions of the EMC Directive Declared as Electronic Independently mounted control, suitable for DIN rail mounting. Intended to mount in remote panel. Type 1.C (Micro-interruption), 330 V rated impulse voltage. 125°C ball pressure test.
	<b>Australia and New Zealand:</b> RCM Mark, Australia/NZ Emissions Compliant
	<b>BACnet International:</b> BACnet Testing Laboratories (BTL) Protocol Revision 12 Listed BACnet Advanced Application Controller (B-AAC)

### LC-VAC110x-0 (Part 1 of 2)

<b>Product Code Numbers</b>	LC-VAC110x-0 Verasys 18 point 240 V Application Controller 120/240 VAC with display
<b>Supply Voltage</b>	120/240 VAC, 50/60 Hz, power supply Class 1 (North America), Safety Extra-Low Voltage (SELV) (Europe)
<b>Power Consumption</b>	<b>20 VA maximum for LC-VAC110x-0</b> <b>Note:</b> VA rating does not include any power supplied to the peripheral devices connected to Binary Outputs (BOs) or Configurable Outputs (COs). This can consume up to 12 VA for each BO or CO; for a possible total consumption of an additional 60 VA (maximum).
<b>Ambient Conditions</b>	<b>Operating:</b> -20°C to 70°C (-4°F to 158°F); 10 to 95% RH noncondensing; Pollution Degree 2 <b>Storage:</b> -40°C to 85°C (-40°F to 185°F); 5 to 95% RH noncondensing.
<b>Addressing</b>	<b>BACnet® MS/TP:</b> Valid field controller device addresses 4–127 Device addresses 0–3 and 128–255 are reserved and not valid field controller addresses. <b>N2:</b> Valid field controller device addresses 1 to 255
<b>Communications Bus</b>	<b>BACnet® MS/TP, ModBus and N2 through RS-485:</b> <ul style="list-style-type: none"> <li>• 3-wire System Bus between the supervisory controller and field controller</li> <li>• 3-wire Sensor Bus between controller, network sensors, and other sensor and actuator devices, includes a lead to source 15 VDC supply power (from controller) to bus devices</li> <li>• 3-wire one Modbus communication half-duplex (Master RTU port)</li> </ul>
<b>Processor</b>	RX631 Renesas® 32-bit microcontroller
<b>Memory</b>	16 MB flash memory and 8 MB RAM

## Verasys® Application Controller (VAC) Catalog Page (Continued)

### LC-VAC110x-0 (Part 2 of 2)

<b>Input and Output Capabilities</b>	<p><b>Five universal inputs:</b> User-configurable, 3 available modes:</p> <ul style="list-style-type: none"> <li>• Voltage input: 0 to 10 VDC</li> <li>• Current sense input: 4 to 20 mA</li> <li>• Resistive inputs/dry contact inputs</li> </ul> <p><b>Four binary inputs:</b> Defined as Dry Contact maintained or Pulse Counter/Accumulator Mode</p> <p><b>Three configurable outputs:</b> User-configurable, 2 available modes:</p> <ul style="list-style-type: none"> <li>• Analog Output: 0 to 10 VDC, 10 mA</li> <li>• Triac Output: 24 VAC, 0.5 A (externally sourced powered)</li> </ul> <p><b>One utility output power port:</b> Ability to deliver 24 VAC</p> <p><b>Four binary outputs (relays):</b> Single-Pole, Single-Throw. Dry contacts rated 240 VAC.</p> <ul style="list-style-type: none"> <li>• UL: 240 VAC, 5 A Resistive, 1.9 LA/11.1LRA, D300 Pilot Duty, 70°C/158°F (30,000 cycles)</li> <li>• IEC: 240 VAC, 3 A Resistive, 3 A Inductive, Cos=0.6, -20°C to 70°C (-4°F to 158°F) (100,000 cycles)</li> </ul> <p><b>Note:</b> Reference all relay commons to the same pole of the supply circuit.</p> <p><b>Two Binary Outputs (Triacs):</b> Output: 24 VAC or 240 VAC, 0.5 A (externally powered)</p> <p><b>Note:</b> Reference all triac commons to the same pole of the supply circuit.</p>
<b>Analog Input/Analog Output Resolution and Accuracy</b>	<p>Analog input: 12-bit resolution          Analog output: 15-bit resolution, +/- 200 mV accuracy in 0 to 10 VDC applications</p>
<b>Terminations</b>	<p>Input/output: Fixed spade terminals          Sensor/System/Modbus: 4-wire and 3-wire pluggable screw terminal blocks          Sensor bus tool port: RJ-12 6-pin modular jack</p> <p><b>Field install option:</b>          Input/output: Fixed solder terminals          Sensor/System/Modbus: 4-wire and 3-wire pluggable screw terminal blocks          Sensor Bus Tool Port: RJ-12 6-pin modular jack</p>
<b>Mounting</b>	<p>Horizontal on single 35 mm DIN rail mount is preferred, or screw mount on flat surface with three integral mounting clips on controller.          Mount the controller on a wall or DIN rail inside an enclosure (rated at least IP20).</p>
<b>Method to Provide Earthing (Grounding)</b>	<p>Functional earthing: Terminal W44</p>
<b>Housing</b>	<p>Enclosure material: Polycarbonate Lexan SABIC EXL9330</p>
<b>Dimensions (H x W x D)</b>	<p>190 mm x 125 mm x 58 mm (7.48 in. x 4.92 in. x 2.28 in.) excluding terminals and mounting clips</p>
<b>Weight</b>	<p>0.5 kg (1.1 lb)</p>
<b>Compliance</b>	<p><b>United States:</b> cULus Listed, File E107041, CCN PAZC, UL 916, Energy Management FCC Compliant to CRF47, Part 15, Subpart B, Class A</p> <p><b>Canada:</b> cULus Listed, File E107041, CNN PAZX7 CAN/CSA C22.2 No.205, Signal Equipment Industry Canada Compliant, ICES-003</p> <p><b>Europe:</b> Johnson Controls declares that this product is also in compliance with the essential requirements and other relevant provisions of the EMC Directive and Low Voltage Directive Declared as Electronic Independently mounted control, suitable for DIN rail mounting. Intended to mount in remote panel. Type 1.C (Micro-interruption) for relays, 2,500 V rated impulse voltage. 125°C ball pressure test.</p> <p><b>Australia and New Zealand:</b> RCM Mark, Australia/NZ Emissions Compliant</p> <p><b>BACnet International:</b> BACnet Testing Laboratories (BTL) Protocol Revision 12 Listed BACnet Advanced Application Specific Controller (B-AAC)</p>




## Verasys® Application Controller (VAC) Catalog Page (Continued)

### LC-VAC300x-0 (Part 1 of 2)

<b>Product Code Numbers</b>	LC-VAC300x-0 Controller 24 V with display
<b>Supply Voltage</b>	24 VAC, 20 VAC minimum/30 VAC maximum, 50/60 Hz, power supply Class 2 (North America), Safety Extra-Low Voltage (SELV) (Europe).
<b>Power Consumption</b>	<b>20 VA maximum</b> <b>Note:</b> VA rating does not include any power supplied to the peripheral devices connected to Binary Outputs (BOs) or Configurable Outputs (COs). This can consume up to 12 VA for each BO or CO; for a possible total consumption of an additional 60 VA (maximum).
<b>Ambient Conditions</b>	<b>Operating:</b> -20°C to 70°C (-4°F to 158°F); 10 to 95% Relative Humidity (RH) noncondensing; Pollution Degree 2. <b>Storage:</b> -40°C to 85°C (-40°F to 185°F); 5 to 95% RH noncondensing
<b>Addressing</b>	<b>BACnet® MS/TP:</b> Valid field controller device addresses 4–127 Device addresses 0–3 and 128–255 are reserved and not valid field controller addresses. <b>N2:</b> Valid field controller device addresses 1 to 255
<b>Communications Bus</b>	<b>BACnet® MS/TP, MODBUS and N2 through RS-485:</b> <ul style="list-style-type: none"> <li>• 3-wire System Bus between the supervisory controller and field controller addresses</li> <li>• 3-wire Sensor Bus between controller, network sensors and other sensor and actuator devices, includes a lead to source 15 VDC supply power (from controller) to bus devices</li> <li>• 3-wire one Modbus communication half-duplex (master RTU port)</li> </ul>
<b>Processor</b>	RX631 Renesas® 32-bit microcontroller
<b>Memory</b>	16 MB flash memory and 8 MB RAM
<b>Input and Output Capabilities</b>	<p><b>Six Universal Inputs:</b> User-configurable, 3 available modes:</p> <ul style="list-style-type: none"> <li>• Voltage input: 0 to 10 VDC</li> <li>• Current sense input: 4 to 20 mA</li> <li>• Resistive inputs/dry contact inputs</li> </ul> <p><b>12 Binary Inputs:</b> Defined as Dry Contact maintained or Pulse Counter/Accumulator Mode</p> <p><b>Four Configurable Outputs:</b> User-configurable, 2 available modes:</p> <ul style="list-style-type: none"> <li>• Analog Output: 0 to 10 VDC, 10 mA</li> <li>• Triac Output: 24 VAC, 0.5 A (externally sourced powered)</li> </ul> <p><b>One Utility Output Power Port (24~ OUT):</b> Ability to deliver 24 VAC</p> <p><b>Four Binary Outputs (Relays):</b> Single-Pole, Single-Throw. Dry Contacts rated 240 VAC</p> <ul style="list-style-type: none"> <li>• UL: 240 VAC 5A Resistive, 1.9 LA/11.1LRA, D300 Pilot Duty, 70°C/158°F (30,000 cycles)</li> <li>• IEC: 240 VAC 3A Resistive, 3A Inductive, Cos=0.6, -20 to 70°C (-4 to 158°F) (100,000 cycles)</li> </ul> <p><b>One Binary Outputs (Relays):</b> Single-Pole, Double-Throw, Dry Contacts rated 240 VAC</p> <ul style="list-style-type: none"> <li>• UL: 240 VAC 5A Resistive, 1.9 LA/11.1LRA, D300 Pilot Duty, 70°C/158°F (30,000 cycles)</li> <li>• IEC: 240 VAC 3A Resistive, 3A Inductive, Cos=0.6, -20 to 70°C (-4 to 158°F) (100,000 cycles)</li> </ul> <p><b>One PWM Output Port:</b> 5 V, 12 V, 15 V selectable PWM output voltage, 10 mA (maximum) continuous current, 100 Hz</p> <p><b>Note:</b> Reference all relay commons to the same pole of the supply circuit.</p> <p><b>Four Binary Outputs (Triacs):</b> Output: 24 VAC or 240 VAC, 0.5 A (externally powered)</p> <p><b>Note:</b> Reference all triac commons to the same pole of the supply circuit.</p>
<b>Analog Input/Analog Output Resolution and Accuracy</b>	Analog Input: 12-bit resolution Analog Output: 15-bit resolution, +/- 200 mV accuracy in 0 to 10 VDC applications
<b>Terminations</b>	Input/Output: Fixed spade terminals Sensor/System/Modbus: 4-wire and 3-wire pluggable screw terminal blocks Sensor Bus Tool Port: RJ-12 6-pin modular jack <b>Field install option:</b> Input/output: Fixed solder terminals Sensor/System/Modbus: 4-wire and 3-wire pluggable screw terminal blocks Sensor Bus Tool Port: RJ-12 6-pin modular jack

## Verasys® Application Controller (VAC) Catalog Page (Continued)

### LC-VAC300x-0 (Part 2 of 2)

<b>Mounting</b>	Horizontal on single 35 mm DIN rail mount (preferred), or screw mount on flat surface with three integral mounting clips on controller. Mount the Verasys Controllers on a wall or DIN rail inside an enclosure (rated at least IP20).
<b>Housing</b>	Enclosure material: Polycarbonate LEXAN® SABIC EXL9330
<b>Dimensions (H x W x D)</b>	220 mm x 125 mm x 58 mm (8.66 in. x 4.92 in. x 2.28 in.)
<b>Weight</b>	0.5 kg (1.1 lb)
<b>Compliance</b>  	<b>United States:</b> cULus Listed, File E107041, CCN PAZX, UL 916, Energy Management Equipment FCC Compliant to CRF47, Part 15, Subpart B, Class A
	<b>Canada:</b> cULus Listed, File E107041, CNN PAZX7 CAN/CSA C22.2 No.205, Signal Equipment Industry Canada Compliant, ICES-003
	<b>Europe:</b> Johnson Controls declares that this product is also in compliance with the essential requirements and other relevant provisions of the EMC Directive and Declared as Electronic Independently mounted control, suitable for DIN rail mounting. Intended to mount in remote panel. Type 1.C (Micro-interruption), 330 V rated impulse voltage. 125°C ball pressure test.
	<b>Australia and New Zealand:</b> RCM Mark, Australia/NZ Emissions Compliant
	<b>BACnet International:</b> BACnet Testing Laboratories (BTL) Protocol Revision 12 Listed BACnet Advanced Application Controller (B-AAC)